



**Remaco MIC-800 Media Interface Controller** designed for user-friendly control of audio-visual equipments. MIC-800 is ideal to be used in Classrooms, Training rooms and Conference rooms which require to control for example LCD projector at a touch of button. It can control simple functions of LCD/ DLP Projector On/Off, Volume and PC sources switching.

### Technical Specifications (MIC-800)

#### ~ Power Supply:

DC 12V power adapter (internal connector)

#### Input:

- ~ PC 1 Signal
  - VGA (D sub 15 pin female)
- ~ PC 1 Audio
  - 3.5mm mini jack
- ~ PC 2 Signal
  - VGA (D sub 15 pin female)
- ~ PC 2 Audio
  - 3.5mm mini jack
- ~ PC 3 Signal
  - VGA (D sub 15 pin female)
- ~ PC 3 Audio
  - 3.5mm mini jack
- ~ 6.35mm MIC IN
- ~ Composite Video Signal-RCA connector
- ~ Composite Audio Signal-RCA connector

#### Output:

- ~ Monitor Out- 350MHz
  - VGA (D sub 15 pin female)
  - Follow by selection of input
- ~ PC signal- 350MHz (internal connector)
- ~ Video signal (internal connector)
- ~ PC Audio (internal connector)
- ~ Video Audio (internal connector)
- ~ RS 232 (internal connector)

#### Feature:

- ~ **Upgraded Version**
  - Able to use Monitor Out & MIC During OFF mode
- ~ **Pre- program Projector Protocol**
  - Easy self programming
  - Selection projector brand by using front button
- ~ **One Touch Selection**
  - LED back lit including sound buzzer
- ~ **Electric Volume Control**
  - Increase or decrease digital volume
- ~ **Signal Amplifier**
  - 350 MHZ

#### Selector:

- ~ Projector On/Off
- ~ MIC On/Off
- ~ PC Selector PC 1/ PC 2/ PC 3
  - (with LED indicator)
- ~ Video Selector (with LED indicator)
- ~ Blank (toggle button)
- ~ Wireless (toggle button)
- ~ Volume Up (digital)
- ~ Volume Down (digital)